

ELECTROZEP

F2000

CONVERTIZOR DE FRECVENTA CU CONTROL VECTORIAL IN BUCLA DESCHISA:



INTRARE	TENSIUNE ALIMENTARE	3-FAZE 400V±15%; MONOFAZAT 230V±15%
	FRECVENTA DE ALIMENTARE	50/60Hz
IESIRE	TENSIUNE IESIRE	3-FAZE 0~ 400V;3-FAZE 0~ 230V
	FRECVENTA IESIRE	0.00~ 650.0Hz
V/F	FRECVENTA PURTATOARE	3000~10000Hz
	REZOLUTIE FRECVENTA	DIGITAL: 0.01Hz, ANALOG: FR MAX X 0.1%
	MOD DE CONTROL	CONTROL VECTORIAL BUCLA DESCHISA (SVC), VV,VF
	CUPLU PORNIRE	0.5Hz/ 150%(SVC)
	CONTROL VITEZA	1:100 (SVC)
	PRECIZIE STABILITATE VITEZA	±0.5%(SVC)
	PRECIZIE STABILITATE CUPLU	±0.5%(SVC)
	SUPRASARCINA	150% CURENTUL NOMINAL, 60 SEC
	RIDICARE CUPLU	AUTOMAT , MANUAL 0.1%~30.0% (VVVF)
	CONTROL V/F	3 MODURI: LINIAR , POLIGONAL , SUPRAFATA , CONFIGURABIL
	FRANARE DC	FRECVENTA DE FRANARE DC: 1.0~5.0 Hz, TIMP DE FRANARE : 0.0~10.0s
	JOGGING	DOMENIU: FR MIN – FR MAX ACCELERATIE : 0.1~3000.0s
	RECIRCULARE SI MULTIVITEZA	16 TREPTE
	CONTROL PI REGLAJ AUTOMAT TENSIUNE (AVR)	CONTROL PI PENTRU BUCLE TENSIUNE DE IESIRE CONSTANTA
	FUNCTII DE CONTROL	REGLARE FRECVENTA
START / STOP		CONTACT LIBER DE POTENTIAL – TERMINALE TASTE COMUNICARE SERIALA
TIPURI DE CONTROL		3 TIPURI: PANOU , TERMINALE , SERIAL
TIPURI DE CONTROL FRECVENTA		PANOU , TERMINALE , ANALOGIC – CURENT , TENSIUNE , POTENTIOMETRU , SERIAL
SURSA FRECVENTA AJUSTARE		REGLAJ FIN 5 TIPURI , FRECVENTA COMPUSA DIN FRECVENTA DE BAZA
PROTECTIE	LIPSA FAZA INTRARE , LIPSA FAZA IESIRE , SUBTENSIUNE , SUPRATENSIUNE DC, SUPRACURENT, SUPRASARCINA , CURENT BLOCARE, SUPRATERMPERATURA, DISTORSIONARE EXTERNA	
AFISAS	LED – FRECVENTA , VITEZA , CURENT IESIRE , TENSIUNE IESIRE , ALARME , PARAMETRI DE PROGRAMARE	
CONDITII DE MEDIU	LOCATIE	LA INTERIOR. SE FERESTE DE UMEZEALA , LICHIDE, VAPORI , PRAFURI , GAZE COROZIVE, GAZE INFLAMABILE, BATAIA DIRECTA A RAZELOR
	TEMPERATURA DE LUCRU	-10~ +50GRC
	UMIDITATE DE LUCRU	< 90% (FARA CONDENSARE)
	VIBRATII	< 0.5g
	ALTITUDINE	< 1000m
MOTOR	0.4~ 400KW	

ELECTROZEP EXIM SRL

TEL. 072.334.04.73 , 0788.444.904...7