

Residual current circuit breaker (RCCB), 40A, 4 p, 30mA, type A

Powering Business Worldwide*

Part no. PF7-40/4/003-A-DE Article no. 263611

Design verification as per IEC/EN 61439

| · | | | |
|------------------------------------------------------------------------------------------------------------------------|------------------|---|----------------------------------------------------------------------------------------------------------------------------------|
| Technical data for design verification | | | |
| Rated operational current for specified heat dissipation | In | Α | 40 |
| Equipment heat dissipation, current-dependent | P _{vid} | W | 9.6 |
| IEC/EN 61439 design verification | | | |
| 10.2 Strength of materials and parts | | | |
| 10.2.2 Corrosion resistance | | | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | | | Meets the product standard's requirements. |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat | | | Meets the product standard's requirements. |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects | | | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | | | Meets the product standard's requirements. |
| 10.2.5 Lifting | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | | | Meets the product standard's requirements. |
| 10.3 Degree of protection of ASSEMBLIES | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | | | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 Internal electrical circuits and connections | | | Is the panel builder's responsibility. |
| 10.8 Connections for external conductors | | | Is the panel builder's responsibility. |
| 10.9 Insulation properties | | | |
| 10.9.2 Power-frequency electric strength | | | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | | | Is the panel builder's responsibility. |
| 10.9.4 Testing of enclosures made of insulating material | | | Is the panel builder's responsibility. |
| 10.10 Temperature rise | | | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 Electromagnetic compatibility | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 Mechanical function | | | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

Technical data ETIM 5.0

| Circuit breakers and fuses (EG000020) / Residual current circuit breaker (RCCB) (EC000003) | ١ |
|--------------------------------------------------------------------------------------------|---|
| on our broakers and rases (Lessesser) residual current on our broaker (1100B) (Lessesse) | , |

Electric engineering, automation, process control engineering / Electrical installation, device / Residual current protection system / Residual current circuit breaker (RCCB)

| (ecl@ss8-27-14-22-01 [AAB906010]) | | | | |
|---------------------------------------------------|----|----------------|--|--|
| Number of poles | | 4 | | |
| Rated voltage | V | V 400 | | |
| Rated current | Α | A 40 | | |
| Rated fault current | А | A 0.03 | | |
| Mounting method | | DIN-rail (DRA) | | |
| Leakage current type | | A | | |
| Selective protection | | No | | |
| Short-circuit breaking capacity (Icw) | kA | kA 10 | | |
| Rated short-circuit breaking capacity EN 60898 | kA | kA 0.5 | | |
| Rated short-circuit breaking capacity IEC 60947-2 | kA | kA 0 | | |
| Surge current capacity | kA | kA 0.25 | | |
| Frequency | | 50 Hz | | |
| Additional equipment possible | | Yes | | |
| Degree of protection (IP) | | IP20 | | |

| Construction size (in accordance with DIN 43880) | | 1 |
|--------------------------------------------------|----|------|
| Width in number of modular spacings | | 4 |
| Built-in depth | mm | 69.5 |
| Short-time delayed tripping | | No |